

PHASE AND MOTOR ROTATION INDICATOR



**CAT III  
600V**

**Part No. C5900**

Taking the guess out of what direction the motor will turn when connecting the power. This multi purpose three phase rotation tester has an additional feature of checking motor rotation. It measures motor rotation by injecting a signal into the motor winding and when the armature is turned the direction will be indicated. In addition C5900 has a non-contact motor rotation facility for 50Hz three phase motors.

- CAT III 600V
- Compact light and easy to use
- Phase and motor rotation indicator
- Non contact phase rotation indication
- Phase live indication

EA QTY 1

<b>Compliance and Safety</b>	Conforms to IEC61010 CAT III 600V, CE
<b>Contents</b>	The C5900 is supplied in a gift box with soft pouch, test leads, crocodile clips & instruction manual.
<b>Dimensions</b>	L124 x W61 x T27mm
<b>Batteries</b>	1 x 9V 6F22
<b>Weight</b>	± 150g
<b>Replacement Test Leads</b>	AL30RYBKIT

Feature	Range
Input Voltage	100 to 600V AC
Frequency	45 to 75Hz

PHASE ROTATION TESTER (NON-CONTACT)



**CAT IV  
600V**

**Part No. C895**


The Phase Rotation Tester (non-contact) is the latest generation phase rotation detector featuring leads with non-contact crocodile clips and is rated CAT IV 600V. The C895 is ideal for testing three phase sequence without a “live” connection. Simply clip the crocodile clip onto the conductors without removing the insulation and the phase sequence and “live” lines are indicated.

- CAT IV 600V, CAT III 1000V
- Visual and Audible Indication
- Non-contact sensor clips
- Indicates Voltage presence 75V to 1000V AC
- AC Frequency 45Hz to 65Hz
- Ideal for overhead lines e.g. ABC
- Auto Power Off - 5 min
- Test Lead Length - 1.5m
- Bright LED for outdoor indication

EA QTY 1

<b>Compliance and Safety</b>	IEC61010-1 CATIII 1000V. EN 61326-1
<b>Contents</b>	Each phase rotation tester has built-in leads and is supplied in a gift box with operating instructions, soft carry bag and battery.
<b>Dimensions</b>	L128 x W72 x T44mm
<b>Batteries</b>	1 x 9 V 6F22
<b>Weight</b>	+ 220g
<b>Test Range</b>	75 to 1000V @ 45 to 65 Hz

PHASE ROTATION TESTER



**CAT III  
500V**

**Part No. T606**

A new design compact phase rotation tester with plug-in leads and electronic circuitry. This unit gives phase and sequence indication. The leads have large crocodile clips that easily clip onto most switchboards. It will identify 3 phases, their sequence and no phase. Used to test supply when installing motors, pumps, conveyor lines, drives, etc.

- Phase and open phase indication
- Plug-in leads
- CAT III 500V
- Easy to use
- Electronic circuits
- No mechanical parts

EA QTY 1

<b>Compliance and Safety</b>	EN61010 CAT III 500V
<b>Contents</b>	The T606 comes in a gift box with soft vinyl case, crocodile clips on plug-in leads, and instruction manual.
<b>Dimensions</b>	L102 x W78 x T32.5mm
<b>Batteries</b>	None
<b>Weight</b>	212g with test leads
<b>Replacement Test Leads</b>	AL30RYBKIT

Feature	Range
Input Voltage	100 to 600V AC
Frequency	45 to 70Hz

In support of our policy of continuous product improvement we reserve the right to change materials and specifications without notice. Drawings, where shown, may not be to scale. Dimensions are metric and size maybe approximate. Where possible data sheets including MSDS are made available on our website and apps. All products should be installed and used in accordance to manufacturer’s instruction provided. Warning: products may be subject of registered designs and patents. Refer to our website or apps for terms and conditions on warranty.